

update-motd ideje

written by js | 2021-10-30

10-who

- #!/bin/bash
- echo ----- `pwd`/\$0 - \$LOGNAME - \$(date +%Y%m%d:%H%M)
 - echo ----- who
- sudo /usr/bin/who --all --ips --process --users --time --heading | ccze --mode=ansi
 - echo ----- w
 - sudo /usr/bin/w -h | ccze --mode=ansi
 - echo ----- last \$LOGNAME
- sudo /usr/bin/last \$LOGNAME -xwan 5 --time-format iso | ccze --mode=ansi
 - echo ----- last root
 - sudo /usr/bin/last root -xwan 5 --time-format iso | ccze --mode=ansi
 - echo ----- users
 - sudo /usr/bin/users | ccze --mode=ansi
 - echo ----- finger
 - sudo /usr/bin/finger | ccze --mode=ansi
 - exit \$?

20-sysinfo

- #!/bin/bash
- echo ----- `pwd`/\$0 - \$LOGNAME - \$(date +%Y%m%d:%H%M)
 - echo --- df
 - sudo df -BG -type=ext4 -type=fuseblk | ccze -A
 - echo --- free
 - sudo free -hwt | ccze -A
 - echo --- s.m.a.r.t.
 - sudo smartctl -health /dev/sda | tail -n 2 | ccze -A
 - echo --- mount
 - sudo mount -verbose -types ext4,fuseblk | ccze -A
 - echo --- vmstat
 - sudo vmstat -w -S M -t | ccze -A
 - echo --- auth.log
 - sudo tail /var/log/auth.log | ccze -A
 - exit \$?

30-senzori

- #!/bin/bash
- echo ----- `pwd`/\$0 - \$LOGNAME - \$(date +%Y%m%d:%H%M)
 - sudo sensors | grep "temp.:" | ccze --mode=ansi
 - echo ----- s-tui
 - sudo s-tui --terminal | ccze --mode=ansi
 - echo ----- inxi
 - sudo inxi -s -c 0 | ccze --mode=ansi
 - exit \$?

Narafski, treba sve ove alatiće prvo instalirati. Pa, instalirajmo..